

## Midas<sup>®</sup> SPECIFICATIONS

### LonWorks<sup>®</sup> Interface Module



Module Dimensions		Midas <sup>®</sup> LonWorks <sup>®</sup> Interface Module
Size (without Midas <sup>®</sup> unit)		120 x 100 x 35mm (H x W x D)
Weight (without Midas <sup>®</sup> unit)		1.0kg
Power Requirements		
Operating Voltage		24VDC Nominal + / - 15%
Output to Midas Transmitter		48VDC via proprietary Power over Ethernet (PoE) connection
Power Consumption		
LonWorks Module		~ 3.0W
Module with Midas		~ 8.0W
Module with Midas & Pyrolyzer		~ 15.0W
Outputs		
Visual		LED indicates network status
Digital Communications		LonWorks <sup>®</sup> digital communication within a 78kbps FTT sub-loop system
Relays		Local activation of three (3) on board Midas <sup>®</sup> relays for fault and alarm or remote activation of 3 relays using LonWorks <sup>®</sup>
Inputs		
Service Test Mode Button		Broadcasts the LonWorks <sup>®</sup> neuron ID
Certification & Specification		
RFI EMC		CE marked: meets EN 5022:1998 Amendment A2 and EN 5024 (24V supply)
Operating Temperature		
Module with Midas Unit		0°C (32°F) to 40°C (104°F)
Wiring Requirement		
Power		16 AWG Maximum 1.5mm <sup>2</sup>
LonWorks <sup>®</sup> Transceiver		FT-10
Warranty		
Module		1 year
Ordering Information		
Midas <sup>®</sup> LonWorks <sup>®</sup> Interface Module		MIDAS-T-LON

#### Find out more

[www.honeywellanalytics.com](http://www.honeywellanalytics.com)

Toll-free: 800.538.0363

#### Please Note:

While every effort has been made to ensure accuracy in this publication, no responsibility can be accepted for errors or omissions. Data may change, as well as legislation, and you are strongly advised to obtain copies of the most recently issued regulations, standards, and guidelines. This publication is not intended to form the basis of a contract.